User's Manual

PNG140 Bluetooth Car Kit

191211R1

Contents:

3 - Overview.
4 - Charging the Battery.
5 - Switching on the car kit.
Pairing with phone.
6 - Multipoint.
7 - Call handling.
Redialing.
Voice Dialing.
8 - Taking second call.
Caution.
Adjust Volume.
Mute.
9 - LED indicator status.
Out of Range
10 - Specification.

Overview:

1- Mute

2- LED mode indicator

3- MIC input

4- Multi-Function Button (MFB)

5- Volume - button

6- Volume + button

7 - Mini USB 5 PIN for the charging socket

8 - Speaker

Before you start using the car kit, you must charge the battery and pair the car kit with a compatible mobile phone.

Charger

This car kit is intended for use with the car charger that is included in the package.

Charging the battery

This device has a Rechargeable Lithium Polymer Battery 3.7V, 750mAH battery.

Connect the car kit to the car charger. The red indicator light is displayed during charging. If charging does not start, disconnect the charger, plug it back in and retry. Charging the battery fully may take up to 2-3 hours.

When the battery is fully charged, the red indicator light turns off. Disconnect the car kit from the charger.

The fully charged battery has power for up to 5 hours of talking time or up to 30 days of standby time. However, the talking and standby time may vary when used with different mobile

phones, products that use a Bluetooth connection, usage settings, usage styles, and environments.

Switching on / off

To switch on, press and hold the "MFB" multi-function button until there is a tone prompt and the blue LED flashes 5 times. The car kit is now on.

To switch off, press and hold the "MFB" for 4 seconds until the red LED flashes 5 times.

Pair the car kit with a compatible phone

- Make sure your car kit is switched off
- Press and hold the "MFB" until the blue and red light flashes alternately and there is a tone prompt. The car kit is now in pairing mode.
- Activate the Bluetooth feature on the phone and set the phone to search for Bluetooth devices. See the user guide of your phone for instructions.
- Select the car kit (PNG140) from the list of found devices.

- Enter the pass code 0000 to pair and connect the car kit to your phone. In some phones you may need to make the connection separately after pairing. See the user guide of your phone for details. You only need to pair the car kit with your phone once.

If the pairing is successful, the car kit's blue light will flash 5 times briefly. The car kit's name appears in the phone menu where you can view the currently paired Bluetooth devices.

Multipoint Pairing

In order to pair a second mobile, please press the volume down button for 3 seconds until the red and blue light flashes alternately; Search for Bluetooth devices from your mobile phone, refer to your phone user manual for pairing with Bluetooth devices. Turn off the PNG140 and back on both phones will automatically be connected.

Basic Use

Call handling

To make a call, use your phone in the normal way when the car kit is connected to your phone, the blue LED will flash during the call.

To answer a call, press the “MFB” and the blue LED will flash during the call.

To reject a call, press the “MFB” for 3 seconds, there is a tone prompt when there is incoming call.

To end a call, press the “MFB” once.

Redialing

Press the volume + key for 3 seconds to redial last dialed telephone number. This function requires that your phone supporting redialing.

Voice Dialing

Press the “MFB” to start voice dialing. This function requires your mobile supporting voice dialing. Check the user manual of your mobile for details.

Taking a second call

You can take a call on a second phone by pressing the mute button. Call on your first will be placed on hold, short press mute button to resume your conversation on first phone.

Caution

Ensure you maintain full control of your vehicle at all times.
Ensure you do not contravene local laws.
Do not be distracted when driving.

Adjust the volume

Press volume + or volume - key to increase or to decrease the volume during a call.

Mute

During a call, press and hold mute button for about 3 seconds to mute the MIC, follow the same operation to withdraw from the MIC mute state.

LED Indicator Status

Switch on: the blue LED flash five times
Standby state: Blue LED flashes twice every 2 second
Connecting status: Blue LED flashes once every 5 second
Making and answering a Call: Blue LED flashes
Call: Blue lights flashing fast
Low battery warning: Red LED flashes 4 times every 30 seconds
Switch off: red LED flashes five times.
Charging state: Red LED always on and it will be off after charging completed.

Out of range

When either of the phones becomes disconnected the PNG140 will alert you with a single audio tone.
Bring both phones within 10m range or closer to the PNG140 will automatically reconnect devices.
In case only one phone being available turn off the PNG140 and back on. The PNG140 will connect to first phone and audio alert will stop.

Specification:

- Bluetooth v2.1+EDR, Class II
- Operating Frequency Band: 2.4GHz ~ 2.48GHz unlicensed ISM band
- Working distance : up to 10 meters
- Integrated with echo cancellation and Noise suppressor
- Built in speaker and microphone
- Battery type: Rechargeable Lithium Polymer Battery 3.7V, 750mAh 2.78Wh
- Charging time : about 2-3 hours
- Talk time : about 5 hours
- Standby time : about 30 days
- Dimensions: 117.5x47x15.3mm
- Pack includes : PNG140, Car Charger, User Manual,
- Pairing: 2 Phones
- Multipoint
- Battery weight 3g

EU

This product is CE certified according to the provision of the R&TTE Directive (99/5/EC).

Declares that this product is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC.

Please note that this product uses radio frequency bands not harmonised within EU.

Within the EU this product is intended to be used in Austria, Belgium, Denmark, Finland, France, Germany, Greece, Ireland, Italy, Luxembourg, The Netherlands, Portugal, Spain, Sweden, and United Kingdom and within EFTA in Iceland, Norway and Switzerland.

Bluetooth is a trademark owned by the Bluetooth SIG, Inc.

Warranty

The condition of this warranty and our responsibilities under this warranty are as follows: Warranty is non-transferable, and is limited to the original purchaser only.

* You must be able to prove the date of original purchase of the unit with a dated receipt.
* The warranty is not applicable if the product has been subject to physical abuse, improper installation, modification or repair by unauthorised third party.
* The responsibility of the supplier’s products shall be limited to the repair or replacement of the product at its sole discretion.
* Specifically exempt from any warranty are limited-life consumable components subject to normal wear and tear, such as batteries and other accessories.
* The Supplier will not take any responsibility if the failure of the unit has resulted from accident, abuse, misuse, or any unauthorised repair, modification or disassemble.
* Modification and repair of the unit this device must be done by an authorised and qualified service centre or returned to the manufacturer.
*This warranty gives you specific legal rights, and you may also have other rights which vary under local laws.

HELPLINE: +44 161 494 4200

WWW.PAMA.COM

The Pama PNG Range is an exclusive selection of Bluetooth handsfree products. Manufactured to the highest possible standards, combining style with functionality to bring you the ultimate handsfree product